Lighting Software Cheat Sheet

Basic Control

This software controls channels by sending each DMX Address a value between 0 and 255.

To Control channels, in "MAIN:" press

```
[channel number][parameter][AT][value][enter]
```

To assign send a value to a parameter

This software has a few different pages. These are

- main (used to control channels and access other menus)
- playback (used to record, playback and view cues)
- patch (add additional fixtures and view currently patched channels)
- settings (view credits and change level)

To access these pages, type each word into the main command line

To return to main page, type "back"

Please feel free to explore this software and if you are curious about how it was built and want to download it for yourself, please scan the QR Code on the didactic.

Recording and playing back Cues

This software allows for users to record cues and play them back. To record a cue press;

```
[playback][enter][record][cue number][enter]
To play back a cue press:
```

```
[playback][enter][record][cue number][enter]
```

Suggested Commands

```
Change colour of SL Bars:

[2][1][RED][AT][2][5][5][ENTER]

[2][2][BLUE][AT][1][2][8][ENTER]
```

```
Change gobo of mover:
```

```
[1][0][1][GOBO1_INDEX][AT][1][6][ENTER]
[1][0][1][GOBO2_INDEX][AT][4][8][ENTER]
```

Change speed of mover:

```
[1][0][1][GOBO1_POSITION][AT][1][3][5][ENTER]
[1][0][1][GOBO1_POSITION][AT][1][5][0][ENTER]
[1][0][1][GOBO1_POSITION][AT][1][9][2][ENTER]
```

Change Intensity of Conventionals

```
[2][AT][2][5][5][ENTER]
[1][AT][6][4][ENTER]
```

<u>Channel List</u>

GLP Gobs	DMX Value		
Gobo 1 wheel			
Open	15		
4 circles	31		
Vertical bars	47		
Quarter circles	63		
Triangles	79		
Dash	95		
Dots	111		
Starry night	126		
Gobo 2 wheel			
Open	15		
Circle	31		
Leaves	47		
Jagged	63		
Shreds	79		
Red and white spiral	95		
Green and yellow	111		
Diamonds	126		

Channel	Fixture	Purpose	Parameters
1	ETC Source 4 JR 25-50deg	Warm Desk Light	Intensity
2	ETC Source 4 JR 25-50deg	Cool Desk Light	Intensity
3	Selecon Acclaim Fresnel 650W	Clothes Rack Top Light	Intensity
11	Selecon SL Par 155 Zoom	Desk Backlight	Intensity, Strobe, Red, Green, Blue, White
21	Selecon SL Bar 510	Clothes Rack Up Light	Intensity, Strobe, Red, Green, Blue, White
22	Selecon SL Bar 510	Clothes Rack Up Light	Intensity, Strobe, Red, Green, Blue, White
101	GLP Impression Spot One	Rug Special and mover	Intensity, Red, Green, Blue, Colour Wheel, Shutter, Gobo, Zoom, Focus, Effect Wheel
201	Generic RGB Fixture	Control Under glow	Red, Green, Blue